

How to burn a new OS into eMMC on Matrix?



Matrix can run Android, Linux and many other operating systems. In order to burn the new OS into eMMC, you are going to need:

- 1x PC
- 1x USB OTG cable

Download the OS image files from the download section of our website to your PC, and then follow a few steps below:

1. Move the "Burn/Run" switcher on the board to the "Burn" side.
2. Connect one end of the USB OTG cable to the OTG port on Matrix, the other end to the USB port of the PC.
3. Open the software "MfgTool2" in the folder, where the OS image files are inside, click "Start", and wait a few minutes until it's completed.
4. Power off Matrix.
5. Move the "Burn/Run" switcher on the board back to the "Run" side.
6. Power on to let Matrix restart, now it can run the new OS you have just burnt into eMMC.